

The system will go through **Device Initialization** and **Startup Wizard** after powering up for the first time. The system will prompt to set the system's language, video standard, system login information as well as the system's general settings.
 Please take note of the new admin password as it can only be reset by email and security questions. If password cannot be recovered, system has to go thru the RMA process and ship to the manufacturer for factory default.

Device Initialization:

Step 1

Language and Video Standard

Step 2

Setup new password - (Please take note of the new password since tech support can't reset the password)

Step 3

Unlock pattern can be used to Login.

Step 4

Email and Security Questions setup. Please make sure to setup these settings for password recovery.

Startup Wizard:

Step 1

Welcome Screen click **Next**.

Step 2

Configure the system's time and date settings to match the location's time zone. Click **Next** to proceed.

Step 3

Change the default TCP/IP settings to match the local network. Click the **Test** button to do a quick test on the configuration. Click **Next** to proceed.

Step 4

Enable P2P for remote viewing as required. The status will say "online" if the network settings are correct. Click **Next** to proceed.

Step 5

Configure the video recording schedule as required. Click **Back** to return to previous step or **Next** to proceed. Then click **Finished**.